

FAG SNV180-F-L + 1317K + H317X300 + FSV617X300参数

|    |       |             |    |          |
|----|-------|-------------|----|----------|
| 说明 |       | FRM180/14.5 |    | 型号, 定位圈  |
|    |       | FSV617.300  |    | 型号, 毛毡密封 |
|    |       | DKV180      |    | 型号, 端盖   |
|    |       | SNV180-F-L  |    | 型号, 轴承座  |
| 尺寸 | $d_1$ | 76.2        | mm | -        |
|    | a     | 380         | mm | -        |
|    | $h_1$ | 223         | mm | -        |
|    | g     | 160         | mm | -        |
|    | b     | 110         | mm | -        |
|    | c     | 40          | mm | -        |
|    | D     | 180         | mm | -        |
|    | $g_3$ | 16          | mm | -        |
|    | h     | 112         | mm | -        |
|    | m     | 320         | mm | -        |
|    | s     | M24         |    | -        |
|    | s     | 22.225      | mm | -        |
|    | u     | 26          | mm | -        |
|    | v     | 32          | mm | -        |
| 重量 | $m_1$ | 17000       | g  | 质量, 轴承座  |
| 说明 |       | 1317K       |    | 型号, 轴承   |
|    |       | H317X300    |    | 质量, 紧定套  |

FAG SNV180-F-L + 1317K + H317X300 + FSV617X300图片





