

### FAG 61900参数

|        |              |       |       |            |
|--------|--------------|-------|-------|------------|
| 尺寸     | d            | 10    | mm    | -          |
|        | D            | 22    | mm    | -          |
|        | B            | 6     | mm    | -          |
|        | $D_1$        | 18.2  | mm    | -          |
|        | $D_{a\ max}$ | 20    | mm    | -          |
|        | $d_1$        | 13.8  | mm    | -          |
|        | $d_{a\ min}$ | 12    | mm    | -          |
|        | $r_{a\ max}$ | 0.3   | mm    | -          |
|        | $r_{min}$    | 0.3   | mm    | -          |
| 重量     | m            | 10    | g     | 质量         |
| 基本额定载荷 | $C_r$        | 2850  | N     | 基本额定动载荷，径向 |
|        | $C_{0r}$     | 1270  | N     | 基本额定静载荷，径向 |
| 极限转速   | $n_G$        | 48000 | r/min | 极限转速       |
| 参考转速   | $n_B$        | 27000 | r/min | 参考速度       |
| 疲劳极限载荷 | $C_{ur}$     | 69    | N     | 疲劳极限载荷，径向  |

### FAG 61900图片





参考资料:<http://www.sozhou.com/p/ce642bc9.html>